


**VII SEMESTER B.TECH. (INFORMATION TECHNOLOGY/ COMPUTER &  
 COMMUNICATION ENGINEERING)**
**END SEMESTER EXAMINATIONS, NOVEMBER 2017**
**SUBJECT: PROGRAM ELECTIVE V - NATURAL COMPUTING [ICT 4011]**
**REVISED CREDIT SYSTEM  
 (25/11/2017)**

Time: 3 Hours

MAX. MARKS: 50

**Instructions to Candidates:**

- ❖ Answer ALL questions.
- ❖ Missing data if any, may be suitably assumed.

- 1A.** Design a Turing Machine to accept the language  $L$ , of strings over  $\Sigma = \{a, b, c\}$  such that  $L = \{a^n b^n c^n \mid n \geq 1\}$  5
- 1B.** Design the transition set for a Pushdown Automata, to accept a language  $L = \{a^n b^{2n} \mid n \geq 0\}$ , over  $\Sigma = \{a, b\}$ . 3
- 1C.** Design a DFA, to accept a language  $L = \{w \mid |w| \bmod 3 \geq |w| \bmod 2\}$ , over  $\Sigma = \{a\}$ , where  $w \in \Sigma^*$ . 2
- 2A.** Explain with the help of an example, the steps involved in the process of designing scaffolded DNA Origami. 5
- 2B.** Compute the function  $f(i, v, j)$  used to solve the SAT problem by abstract Tile Assembly Model, for the formula  $F = (x \vee y \vee z) \wedge (\bar{x} \vee \bar{y} \vee \bar{z}) \wedge (\bar{x} \vee \bar{y} \vee z)$ , given  $i = (1, 0, 1)$  and  $v = (x, y, z)$ . 3
- 2C.** Demonstrate the subset construction method to convert the following NFA (transitions shown in Table Q.2C) to DFA. 2

Table Q.2C

$\delta$	0	1
$\rightarrow A$	$\{A, B\}$	$\{A, C\}$
B	$\{D\}$	$\emptyset$
C	$\emptyset$	$\{D\}$
*D	$\{D\}$	$\{D\}$



- 3A. Explain in detail the steps involved in Paddy Field Algorithm. 5
- 3B. Demonstrate the generation of a binary counter using the DNA Tile Assembly Model. 3
- 3C. Describe with the help of an example the process used in extracting the result in Adleman's approach of solving the Hamiltonian Path Problem in a graph. 2
- 4A. Apply the DNA Computation operations to solve the minimal cover set problem using the sticker model for the given data. Objects = {1, 2, 3, 4, 5} and Bags = {{1, 2, 4}, {2, 5, 4}, {2, 4}, {1, 3, 5}}. Indicate all the steps along with the DNA operations. 5

- 4B. Compute the evolution of the cells for time  $t = 1, 2$  using the rules of game of life and **periodic boundary condition** for the given Cellular Automata at  $t = 0$  in Fig. Q.4B, and also state its configuration. [Note: Shaded cells are dead cells] 3



Fig. Q.4B

- 4C. Illustrate with the help of a quantum circuit how the bell states can be generated. 2
- 5A. Design a P-system of degree 4 that generates  $n^2$ , for any integer  $n \geq 1$ . Show the computations for  $n = 1$  and  $n = 3$ . 5
- 5B. Compute the unitary operation performed by the circuit given in Fig. Q.5B, given two single qubit gates,  $U_1 = \begin{bmatrix} a & c \\ b & d \end{bmatrix}$  and  $U_2 = \begin{bmatrix} e & g \\ f & h \end{bmatrix}$ . Write the  $4 \times 4$  matrix for the unitary operation. 3




Fig. Q.5B

- 5C. Describe how peptide computing can be used to compare the quantity of an element in two multisets. 2