

Question Paper

Exam Date & Time: 18-Apr-2018 (09:30 AM - 12:30 PM)



MANIPAL ACADEMY OF HIGHER EDUCATION

INTERNATIONAL CENTRE FOR APPLIED SCIENCES

FOURTH SEMESTER B.S (ENGG)

END-SEMESTER THEORY EXAMINATIONS APRIL - 2018

DATE : 18 APRIL 2018

TIME : 9:30AM TO 12:30PM

Analysis And Control Of Electromagnetic Devices [EE 242]

Marks: 100

Duration: 180 mins.

Answer 5 out of 8 questions.

- 1) Mention the properties of an ideal transformer (4)
 - A)
 - B) Obtain the condition for zero voltage regulation of a transformer. (4)
 - C) An 11 kV, 3 Phase, star - connected synchronous motor is taking a current of 200 A at unity power factor. The excitation is decreased by 20%. Find the new current and PF. Assume constant load and synchronous reactance of 9Ω . (12)
- 2) Draw and explain the torque / slip characteristics of a 3 Phase induction motor. (6)
 - A)
 - B) Obtain the condition for maximum torque and the maximum torque. (6)
 - C) A 3 phase, 4 pole, 50 Hz, star connected 220 V induction motor has rotor resistance of 0.2Ω and rotor reactance of 1Ω . The ratio of stator to rotor turns is 2. Find the torque developed at 4 % slip and 20 % slip. (8)
- 3) Distinguish between squirrel cage rotor and slip ring rotor. (4)
 - A)
 - B) What is the necessity of a starter for 3 phase induction motor? With a neat sketch explain the star/delta starter. (6)
 - C) A 250 V delta connected synchronous motor has an excitation voltage of 350 V. Find the H_p output, input current and PF. Assume a load angle of 30° , $Z_s = (0.5 +$ (10)

j5) Ω .

- 4) What is the significance of All-day Efficiency? (4)
- A)
- B) With sketches prove that the speed of the rotating field is inversely proportional to number of poles. (6)
- C) A 15 kVA transformer is loaded as follows (10)
- 12 hours - 2 kW at PF of 0.5
- 6 hours - 12 kW at PF of 0.8
- 6 hours - 18 kW at PF of 0.9
- Find the all-day efficiency
- Iron loss = full load copper loss = 300 W.
- 5) A 1000 kVA, 3 Phase load works at a power factor of 0.8 lag. Find the kVA rating of the synchronous motor to make the overall PF 0.98 lag. The synchronous motor has a load of 50 kW with an efficiency of 90 %. (10)
- A)
- B) Determine the iron loss and full load copper loss of a 1 kVA, 50 Hz, 200/400 V transformer. (10)
- The efficiency is 0.88 both at 50 % of full load and 131 % of full load. Assume UPF load. Also find the load kVA at maximum efficiency.
- 6) Explain the significance of O.C & S.C tests on a transformer. (3)
- A)
- B) Determine R_c , X_m , R_{eq} , X_{eq} referred to primary of a 4 kVA, 200/400 V, 50 Hz transformer with the following test results. (10)
- O.C Test 200V, 0.7 A, 70 W (LV Side)
- S.C Test 15V, 5 A, 20 W (HV Side)
- Also find the efficiency at full load 0.8 PF lag.
- C) Find the line current of a 3 phase, 50 Hz, Δ connected 20 hp, 400 V induction motor stated using Y/ Δ starter. Full load efficiency = 0.8, Full load PF = 0.85. (7)
- The short circuit line current is 5 times the full load value. Slip at full load is 5%. Also find the ratio of starting torque / full load torque.
- 7) Derive the expression for the power output of a synchronous motor in terms of E , V , δ & θ . Find the condition for maximum output neglecting resistance. (10)
- A)
- B) The power input to a 500 V, 50 Hz, 6 Pole, 3 phase (10)

induction motor running at 975 RPM is 35 kW. The stator losses are 1.5 Kw. Calculate

- a) Slip output b) Rotor copper loss c) hp
d) line current frequency e) Efficiency f) Rotor frequency

Assume full load power factor = 0.85 lag.

- 8) A 4 kVA, 200/400V, 50 Hz transformer has an impedance of $(1+j3)\Omega$ referred to secondary, Find the % regulation at full load and the following power factors. (6)
- A) a) 0.8 PF lag b) 0.8 PF lead c) unity PF.
Comment on results.
- B) The rotor resistance and reactance per phase of a 4 pole, 50 Hz, 3 phase induction motor are 0.25Ω and 1Ω respectively. (6)
Find the value of external resistance to get a) 50% of maximum torque at starting b) Maximum torque at starting.
- C) Draw and explain the phasor diagram of a transformer supplying a) a lagging PF load b) Unity PF load (8)

-----End-----